

D7212GV3 Control Panel

www.boschsecurity.com



BOSCH
Invented for life



- ▶ Fully integrated intrusion and fire functions allow users to interface with one system instead of two
- ▶ Conettix IP-based communication options provide high-speed, secure alarm transport and control through connection of up to two wired (DX4020) and/or wireless (ITS-DX4020-G) network interfaces
- ▶ Four programmable areas with perimeter and interior partitioning
- ▶ 40 points with flexible configuration options to meet application specific requirements
- ▶ Commercial Wireless allows up to 32 RF points

The D7212GV3 Control Panel delivers a powerful new solution for intrusion (commercial and residential) and residential fire alarm system applications. Monitor alarm points for intruder or fire alarms while operating user command centers and other outputs. The D7212GV3 Control Panel includes a communicator that sends event reports to selected public switched telephone network (PSTN), IP network, or general packet radio service (GPRS) destinations through four programmable route groups. Program all system functions locally or remotely (attended or unattended) through Remote Programming Software (RPS); program critical parameters on site through a keypad. The D7212GV3 Control Panel provides up to 40 individually identified points. Each point accommodates normally-open and normally-closed devices with end-of-line (EOL) resistor supervision. Each point is programmable for fire, fire supervisory, or intrusion applications.

Functions

Programmable Outputs

- 2 A alarm power at 12 VDC
- 1.4 A auxiliary power at 12 VDC
- Four alarm output patterns

- Automatic bell test
- Three on-board outputs, 24 off-board programmable outputs

System Response

- High performance micro-controller provides industry leading system response
- 31 custom point indexes, including fire supervisory
- Selectable point response time
- Cross point capability
- Fire alarm verification
- Watch mode
- Scheduled events (skeds) arm, disarm, bypass and unbypass points, control relays, and control authority levels

Area Configurations

Area programming offers a wide selection of different system configurations. Each area is assigned an account number to define annunciation, control, and reporting functions. Multiple areas can be linked to a shared area which is automatically controlled (hallway or lobby). Area arming can be conditional on other areas (master or associate). Any area can be configured for perimeter and interior arming, not requiring a separate area for this function.

User Interface

- Supervises up to eight command centers (up to 32 non-supervised command centers can be used)
- Custom keypad text is fully programmable, including remote programming
- Four custom functions
- Full function command menu including custom functions
- Each user has authority by area and 16-character name
- 14 custom authority levels control user's authority to change, add, delete passcodes, delete access control tokens, delete cards, disarm, bypass points, and initiate system tests
- Up to 40 programmable, scheduled events and up to 16 event functions for controlling relays, enabling passcodes and windows, and automatically arming and disarming areas
- Adjustable brightness or volume for command center display or sounder
- One parallel printer

The D7212GV3 provides on-premises point and system status annunciation. The fully selectable user interface customizes command center displays and allows users to create appropriate menu items and functions. Function lists can help a user become familiar with the operation of the control panel and custom functions allow users to perform complex functions with a few keystrokes. Each function can be programmed and identified by sixteen characters of custom text and can contain up to 32 keystrokes.



Notice

At least one command center per system is recommended.

Two Man Rule

Two Man Rule requires two unique passcodes on the same command center to disarm an area. Without the second passcode, the system denies entry. Two Man Rule requires the presence of two people at opening, providing added security.

Early Ambush

Early Ambush requires two passcode entries on the same command center. Enter the same passcode twice or have two unique passcodes, depending on the configuration. The first entry disarms the area and the second entry stops a timer programmed to send a duress event. If the second entry does not occur within the programmed time, the system generates a duress event. Early Ambush allows users to inspect the premises and use the system to confirm that the area is safe to enter, providing added security.

Easy Exit Control

The D7212GV3 Control Panel changes from one armed state to another armed state without disarming. For example, if you change the state from Master Arm to

Perimeter Arm, the control panel complies and reports the change. Easy Exit Control reduces the number of keystrokes, simplifying system operation.

Programmable Passcode-controlled Menu List

The system prompts users to enter a passcode prior to viewing the command center menu. The command center display shows the user the menu options allowed according to the user's authority level. Passcode-controlled menus provide users only with the options and information pertinent to them, simplifying system operation.

Passcode Follows Scope

Use Passcode Follows Scope to restrict passcode arming and disarming only to the command center's immediate local area, even if the command center can report events from other areas. Passcode Follows Scope simplifies the arming and disarming procedure without limiting any other command center command capabilities.

Passcodes

User passcodes contain three to six digits. Assign each user one of 14 customized authority levels in each area. Restrict passcodes to operate only during certain times.

The Two Man Rule and Early Ambush options require two passcodes, providing additional security in financial establishments such as banks.

Communications

The D7212GV3 prioritizes and sends reports to four route groups. Each group has a programmable primary and backup destination.

The D7212GV3 provides flexible communications for most central stations with reporting capabilities such as:

- Individual point numbers
- Opening or closing reports by user and area number
- Remote programming attempts
- Diagnostic reports

The D7212GV3 uses the DX4020 Ethernet Network Interface Module and/or the ITS-DX4020-G GPRS/GSM Communicator to communicate with the Conettix D6600 and D6100i Communications Receiver/Gateways. Using Conettix IP communication offers a secure path that includes anti-replay/anti-substitution features and provides enhanced security with encryption. Both the DX4020 and ITS-DX4020-G can be used for remote programming.

Security and Fire Detection

The D7212GV3 Control Panel provides eight on-board points, and up to 32 additional off-board points (depending on model and expansion interfaces). You can program individual points to monitor all types of burglar alarms, fire alarms, and supervision devices.

Commercial Wireless

The Commercial Wireless platform, powered by Inovonics wireless mesh network technology, ensures superior range, reliability, and scalability for

commercial applications. Using a wide range of transmitters and repeaters, this proven technology provides flexibility and performance to meet the most stringent requirements. This exclusive protocol is available only on Commercial Wireless products. The Commercial Wireless platform sends redundant information on several multi-frequency channels within the FCC Part 15 900 MHz band, providing superior range and reliability. In comparison, systems that use a single frequency technology can only send information on one narrow band channel. Any interference within the band can cause missed signals. With wireless registration, it is easy to add this technology to any application.

Event Log

The event log stores up to 1,000 local and transmitted events. The event log includes time, date, event, area, point, and user number. View the event log from select command centers or remotely retrieve event information using RPS. RPS operators can retrieve events periodically using one phone call, rather than receiving several calls each day. When the event log reaches a programmed threshold of stored events, it can send an optional report to a receiver.

Scheduled Events (Skeds)

The internal clock and calendar start individually scheduled events (skeds). Skeds perform functions such as arm or disarm, relay control, or point bypassing. The D7212GV3 Control Panel offers:

- 40 scheduled events with up to 16 different functions available
- Eight opening windows and eight closing windows
- Eight user windows
- Day-of-week, date-of-month, or holiday only schedules
- Four holiday schedules of 366 days each (leap year)

Fire Test

When a user activates Fire Test Mode, the control panel suppresses all reports to the central station. The command center and annunciator show all testing data. An automatic sensor reset feature saves time; you do not need to reset the sensors manually. At the end of test, the command center shows the number of untested points.

Programming, Diagnostics and Controls

Installers can do limited programming on-site with a keypad (critical parameters; such as, .Account IDs, Central Station and RPS IP addresses and phone numbers, reporting formats, and such). They can also do full programming on-site or remotely (attended or unattended) with RPS. A programmable system passcode prevents unauthorized remote programming. D7212GV3 Control Panels accommodate up to four separate destinations for primary, alternate, and backup receivers for automatic test reports. When resetting alarms or arming or disarming a system, the user is identified by name and number.

ROM Updates

An on-site flash update key provides for easy feature enhancements without replacing ROM chips.

Certifications and approvals

FCC		Designed to comply with Part 15
Region	Certification	
USA	UL	AMCX: Central Station Alarm Units (ANSI/UL 1610 and 1635); AMTB: Control Panels, SIA False Alarm Reduction (UL 864 and ANSI/SIA CP-01-2000); AOTX: Local Alarm Units (ANSI/UL 609 and ANSI/UL 464); APAW: Police Station Alarm Units (ANSI/UL 365 and ANSI/UL 464); APOU: Proprietary Alarm Units (ANSI/UL 1076); NBSX: Household Burglar Alarm System Units (ANSI/UL 1023); UTOU: Control Units and Accessories, Household System Type (ANSI/UL 985)
	CSFM	see our website

Installation/configuration notes

Compatible Products

Keypads

D1260 Series Keypads
(D1260, D1260W, D1260R, D1260BLK, D1260B)

D720 Series Keypads
(D720, D720W, D720R, D720B)

D1255 Series Keypads
(D1255, D1255W, D1255B)

D1265 Touch Screen Keypad

D279A Independent Zone Control

Detectors

D278S Four-wire Addressable Detector Base

D285/TH Photoelectric Smoke Detector Heads

D298S Addressable Detector Base

D7050 Series Addressable Photoelectric Smoke and Smoke Heat Detector Heads

F220-B6PM/S Addressable Detector Bases with POPITs

MX775i Addressable PIR Detector

MX794i Long Range Multiplex PIR Detector

MX934i Addressable PIR Detector

MX938i Addressable PIR Detector

ZX776Z PIR Detector

ZX794Z Long Range PIR Detector

ZX835 TriTech Microwave/PIR Detector

ZX935Z PIR Detector

ZX938Z PIR Detector

ZX970 PIR/Microwave Detector

Bosch conventional detectors, including Blue Line, seismic, PIR, TriTech PIR Microwave, photoelectric, heat, and smoke.

Enclosures

D8103 Universal Enclosure

D8108A Attack-Resistant Enclosure

D8109 Fire Enclosure

Magnetic Contacts

Bosch magnetic contacts include recessed, terminal connection, miniature, overhead door, and surface mount.

Modules

Conettix ITS-DX4020-G GPRS/GSM Integrated Communicator

Conettix DX4020 Network Interface Module

Conettix DX4010V2 USB/Serial Interface Module

Conettix C900V2 Dialer Capture Module

D113 Battery Lead Supervision Module

D125B Dual Class B Initiating Module

D127 Reversing Relay Module

D129 Class A Initiating Module

D130 Auxiliary Relay Module

D185 Reverse Polarity Signaling Module

D192G Notification Appliance Circuit Module

D928 Phone Line Switcher

D5060 MUX Programmer

D8125 POPEX Point Expander

D8128D OctoPOPIT Eight Point Expander

D8125MUX Point Expander

D8125INV Wireless Interface Module

D8129 Octo-relay Module

D8130 Door Release Module

D9127 Series POPIT Modules

D9131A Parallel Printer Interface Module

DS7432 Eight-input Remote Module

DS7457i Series Single Zone Multiplex Input Modules

DS7460i Two-input Module

DS7461i Single-input Multiplex Module

DS7465i Input and Output Module

Communications Formats

Modem IIIa²

Contact ID

Programming

Remote Programming Software (RPS)

Commercial Wireless Products

ISW-D8125CW Commercial Wireless Interface

ISW-EN7280 Serial Receiver

ISW-EN4200 Serial Receiver

ISW-EN4204R LED Receiver

ISW-EN4216R LCD Receiver

ISW-EN4016SK Survey Receiver

ISW-EN5040-T High-power Repeater

ISW-EN1210 Universal Transmitter (Single-input)

ISW-EN1210EOL Universal Transmitter with EOL Resistor

ISW-EN1210SK Survey Transmitter

ISW-EN1210W Door-Window Transmitter with Reed Switch

ISW-EN1215EOL Universal Transmitter with Wall Tamper and EOL Resistor

ISW-EN1215WEOL Door-Window Transmitter with Wall Tamper, Reed Switch, and EOL Resistor

ISW-EN1223D Water-resistant Pendant Transmitter (Double-button)

ISW-EN1223S Water-resistant Pendant Transmitter (Single-button)

ISW-EN1223SK Survey Pendant Transmitter

ISW-EN1233D Necklace Pendant Transmitter (Double-button)

ISW-EN1233S Necklace Pendant Transmitter (Single-button)

ISW-EN1235D Beltclip Pendant Transmitter (Double-button)

ISW-EN1235S Beltclip Pendant Transmitter (Single-button)

ISW-EN1235DF Fixed-location Transmitter (Double-button)

ISW-EN1235SF Fixed-location Transmitter (Double-button)

ISW-EN1242 Smoke Detector-Transmitter

ISW-EN1247 Glassbreak Sensor-Transmitter

ISW-EN1249 Billtrap Transmitter

ISW-EN1260 PIR Motion Sensor Transmitter (Commercial and High-end Domestic Applications)

ISW-EN1261HT PIR Motion Sensor Transmitter (High-traffic Areas)

ISW-EN1262 PIR Motion Sensor Transmitter (Residential and Low-traffic Commercial Applications)

ISW-EN1265 PIR Motion Sensor Transmitter (Ceiling-mount Applications)

Parts included

Quant.	Component		
1	D7212GV3 Board		
1	Mounting Skirt		
1	Faceplate with D7212GV3 Label		
1	Literature pack <ul style="list-style-type: none"> • Installation Instructions • Owners Manual • Release Notes 		
1	Literature CD containing all product literature		
		Kits	
	Components	-K1	-K1W
	D7212GV3 Board	1	1
	D101 Lock and Key Set	1	1
	D1255 Keypad	1	
	D1255W Keypad		1
	D1260 Keypad		
	D1640 Transformer	1	1
	D8103 Enclosure	1	1
	DS835i PIR Detector	2	2
		Kits	
	Components	-K6	-K7
	D7212GV3 Board	1	1
	D101 Lock and Key Set	1	1
	D1255 Keypad		1
	D1255W Keypad		
	D1260 Keypad	1	
	D1640 Transformer	1	1
	D8103 Enclosure	1	1
	DS835i PIR Detector		1
	D8128D OctoPOPIT Eight-point Expander		1
	Conettix DX4020 Ethernet Network Interface Module	1	

Technical specifications

Communications

SDI Bus A (+):	9 VDC 4572 m (15,000 ft)
SDI Bus B (-):	9 VDC 4572 m (15,000 ft)
Telephone Connection:	RJ31X or RJ38X

Electrical

Current Draw (Minimum):	200 mA
Current Draw (Maximum):	500 mA
Output (Alarm):	2 A at 12 VDC
Output (Auxiliary, Continuous Power, and Switched Auxiliary combined):	1.4 A at 10.2 VDC to 13.9 VDC
Voltage (Operating):	12 VDC
Voltage (AC):	16.5 VAC 40 VA plug-in transformer (D1640)
Voltage (DC):	<ul style="list-style-type: none"> • Up to 2 12 VDC, 7 Ah sealed lead acid rechargeable batteries • Up to 2 12 VDC, 18 Ah sealed lead acid rechargeable batteries

Environmental

Relative Humidity:	5% to 85% at +30°C (+86°F), non-condensing
Temperature (Operating):	0°C to +50°C (+32°F to +120°F)

Number of...

Areas:	4
Custom Functions:	4
Programmable Relay Outputs:	27
Events:	Store up to 1,000
Parallel Printers:	1
Passcode Users:	99, plus 1 service passcode
Points:	40 (eight on-board, up to 32 off-board)
RF Points:	32
SKEDs:	40

Trademarks

Trademark names are used throughout this document. In most cases, these designations are claimed as trademarks or registered trademarks in one or more countries by their respective owners. Rather than placing a trademark symbol in every occurrence of a trademark name, Bosch Security Systems, Inc. uses the names only in an editorial fashion and to the benefit of the trademark owner with no intention of infringing the trademark.

Inovonics is a trademark of Inovonics Wireless Corporation.

Ordering information

D7212GV3 Control Panel

Includes one printed circuit board (PCB) with mounting skirt and faceplate with label, and a literature pack and CD.

Order number **D7212GV3**

D7212GV3K1 Burglar Kit with D1255

Contains one PCB, one lock and key set, one transformer, one universal enclosure, two PIR detectors, and one D1255 Keypad.

Order number **D7212GV3K1**

D7212GV3K1W Burglar Kit with D1255W

Contains one PCB, one lock and key set, one transformer, one universal enclosure, two PIR detectors, and one D1255W Keypad.

Order number **D7212GV3K1W**

D7212GV3K6 Burglar Kit with D1260

Contains one PCB, one lock and key set, one transformer, one universal enclosure, one D1260 Keypad, and one Conetix DX4020 Ethernet Network Interface Module.

Order number **D7212GV3K6**

D7212GV3K7 Burglar Kit with D8128D

Contains one PCB, one lock and key set, one transformer, one universal enclosure, one D1255 Keypad, one PIR detector, and one OctoPOPIT eight-point expander.

Order number **D7212GV3K7**

Accessories

ICP-SDI-9114 SDI Splitter

Provides the ability to set up two independent SDI buses from a single SDI connection on the control panel.

Order number **ICP-SDI-9114**

ICP-EZTS Dual Tamper Switch

Combination tamper switch with a wire loop for additional tamper outputs.

Order number **ICP-EZTS**

D101 Lock and Key Set

Short-body lock set with one key supplied. Uses the D102 (#1358) replacement key.

Order number **D101**

D122 Dual Battery Harness

Harness with circuit breaker. Connects two batteries to a compatible control panel.

Order number **D122**

D122L Dual Battery Harness with Long Leads

Color-coded harness with circuit breaker and leads measuring 89 cm (35 in.). Connects 12 V batteries to compatible control panels.

Order number **D122L**

D126 Standby Battery (12 V, 7 Ah)

A rechargeable sealed lead-acid power supply used as a secondary power supply or in auxiliary or ancillary functions.

Order number **D126**

D1218 Battery (12 V, 18 Ah)

A 12 V sealed lead-acid battery for standby and auxiliary power with two bolt-fastened terminals. Includes hardware for attaching battery leads or spade connectors

Order number **D1218**

D1224 Battery (12 V, 26-28 Ah)

A 12 V sealed lead-acid battery for standby and auxiliary power with two bolt-fastened terminals. Includes hardware for attaching battery leads or spade connectors.

Order number **D1224**

D136 Plug-In Relay

Maximum rating is 1 A at 24 VDC or 2 A at 12 VDC. Available individually (D136) or in a package of 25 (D136-25).

Order number **D136**

D137 Mounting Bracket

Used to mount accessory modules in D8103, D8108A, and D8109 enclosures.

Order number **D137**

D138 Mounting Bracket, Right Angle

Used to mount accessory modules in D8103, D8108A, and D8109 enclosures.

Order number **D138**

D1640 Transformer

System transformer rated at 16.5 VAC, 40 VA.

Order number **D1640**

D8103 Enclosure

Grey steel enclosure measuring 41 cm x 41 cm x 9 cm (16 in. x 16 in. x 3.5 in.).

Order number **D8103**

D8108A Attack Resistant Enclosure

Grey steel enclosure measuring 41 cm x 41 cm x 9 cm (16 in. x 16 in. x 3.5 in.). UL Listed. Includes lock and key set. B520, B4512, and B5512 require the B12 mounting plate.

Order number **D8108A**

D9002-5 Mounting Skirt

Mounts inside D8103, D8108A, and D8109 enclosures. Can accept up to six standard 7.62 cm x 12.7 cm (3 in. x 5 in.) cards.

Order number **D9002-5**

Software Options

RPS Kit (USB)

Account management and control panel programming software with USB security key (dongle).

Order number **D5500C-USB**

Represented by:

Americas:

Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
security.sales@us.bosch.com
www.boschsecurity.us

Europe, Middle East, Africa:

Bosch Security Systems B.V.
P.O. Box 80002
5617 BA Eindhoven, The Netherlands
Phone: + 31 40 2577 284
Fax: +31 40 2577 330
emea.securitysystems@bosch.com
www.boschsecurity.com

Asia-Pacific:

Robert Bosch (SEA) Pte Ltd, Security Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia

China:

Bosch (Shanghai) Security Systems Ltd.
201 Building, No. 333 Fuquan Road
North IBP
Changning District, Shanghai
200335 China
Phone +86 21 22181111
Fax: +86 21 22182398
www.boschsecurity.com.cn

America Latina:

Robert Bosch Ltda Security Systems Division
Via Anhanguera, Km 98
CEP 13065-900
Campinas, Sao Paulo, Brazil
Phone: +55 19 2103 2860
Fax: +55 19 2103 2862
latam.boschsecurity@bosch.com
www.boschsecurity.com