

# FX82011 Ethernet Media Converter

## ONE 10BASE-T/100BASE-TX PORT AND ONE 100BASE-FX FIBER PORT

### Product Features

- Ethernet Media Converter:
  - One 10Base-T/100Base-TX Port
  - One 100Base-FX Port That Accepts Two Fibers
- Converts 10Base-T/100Base-TX Ethernet Data to 100Base-FX Ethernet Data and Vice Versa
- Compatible with Third-Party 100Base-FX Ethernet Equipment (Multimode ST and SC Models Only)
- Designed for Point-to-Point Applications
- User-Selectable 10Base-T/100Base-TX Port Functions:
  - Autonegotiation Between 10 Mbps and 100 Mbps Data Rates and Between Full-Duplex and Half-Duplex Modes
  - 10 Mbps or 100 Mbps Selectable
  - Full-Duplex or Half-Duplex Mode Selectable
  - Enabling/Disabling of Flow Control
- Auto MDI/MDI-X (Medium Dependent Interface/Medium Dependent Interface Crossover) Operation
- Link-Down Detection
- Compliant with IEEE 802.3, 802.3u, and 802.3x Standards
- Multimode Fiber Support for Distances up to 6 km
- Single-Mode Fiber Support for Distances up to 46 km
- Laser Diode for Transmission of Optical Signals
- Environmentally Hardened

The **FX82011** media converter converts 10Base-T/100Base-TX Ethernet data to 100Base-FX Ethernet data and vice versa. Designed for point-to-point applications, the **FX82011** media converter provides one 10Base-T/100Base-TX port and one 100Base-FX fiber port. Two fibers are required to transport bidirectional data over the 100Base-FX fiber port.

The 100Base-FX fiber port is automatically forced to full-duplex 100 Mbps operation. Networking functions for the 10Base-T/100Base-TX port (RJ-45 twisted-pair copper port) are user-selectable by means of a rotary switch. Autonegotiation allows the port to automatically negotiate between 10 Mbps and 100 Mbps data rates and between full-duplex and half-duplex modes. If autonegotiation is not desired, the port can be forced to specific modes of operation: 10 Mbps or 100 Mbps data rate, half-duplex or full-duplex mode, and the enabling/disabling of flow control. The auto MDI/MDI-X feature allows the RJ-45 port to connect to either a straight-through or crossover RJ-45 cable.



- Designed to Meet NEMA TS 2 and Caltrans Traffic Signal Control Equipment Environmental Standards
- No Performance Adjustments Required
- 12 VDC or 24 VAC Power Supply
- Stand-Alone and Rack-Mountable Modular Design
- LED Indicators for Monitoring of Optic Signal/Laser Status, 100Base-FX Port Status Including Far End Fault Indication (FEFI), 10Base-T/100Base-TX Port Status, and Operating Power

The link-down detection feature of the media converter propagates a link-down status among all 10Base-T/100Base-TX and 100Base-FX ports connected in the network when a 10Base-T/100Base-TX link or 100Base-FX link goes down. As a result, all ports are disabled and data transmission halts until the faulty link is restored.

Modular in design, the **FX82011** unit can be rack mounted or can be used as a stand-alone module. Rack mounting is accomplished using the RK5000 Series rack mount chassis. As a stand-alone module, the unit can be placed on a desktop or can be mounted to a wall.



C2625 / NEW 1-08



International Standards Organization Registered Firm; ISO 9001 Quality System



# TECHNICAL SPECIFICATIONS

## MODELS

Model Number	Fiber Optic Connector Type	Number of Fibers	Wavelength (Transmit/Receive)	Optical Power Budget	Maximum Transmission Distance	Supplied Accessories
<b>Multimode (62.5/125 μm)</b>						Regulated switching power supply with multiple plug adapters (North American, Australian, United Kingdom, and European); 100-240 VAC, 50-60 Hz input, 12 VDC output
FX82011MSTR-2	ST	2	1310/1310 nm	26 dB*	6 km (3.7 mi) <sup>†</sup>	
FX82011MSCR-2	SC	2	1310/1310 nm	26 dB*	6 km (3.7 mi) <sup>†</sup>	<b>Note:</b> In extreme temperature conditions, it is recommended that an industrial-rated outdoor power supply be used.  Wall clip for attachment of single module to wall
<b>Single-Mode (9/125 μm)</b>						
FX82011SSTR-2	ST	2	1310/1310 nm	28 dB	46 km (28.6 mi) <sup>‡</sup>	
FX82011SSCR-2	SC	2	1310/1310 nm	28 dB	46 km (28.6 mi) <sup>‡</sup>	
*When using 50/125 μm multimode fiber, subtract 3 dB from the optical power budget. <sup>†</sup> Maximum transmission distance is limited by fiber bandwidth. <sup>‡</sup> Maximum transmission distance is based on attenuation of 0.5 dB/km plus a 5 dB buffer for connector and splice losses.						
<b>Notes:</b> <ul style="list-style-type: none"> <li>• Single-mode FC connector is available upon request. Contact the factory for additional information.</li> <li>• For conformal coated models, replace the first letter <i>F</i> in the model number with the letter <i>C</i>. The conformal coated version of FX82011MSTR-2, for example, is CX82011MSTR-2.</li> <li>• For models with higher optical power budgets, contact the factory.</li> </ul>						

## PERFORMANCE

Switch Type	Unmanaged Layer 2
Switch Method	Store and forward
Data Rate	10/100 Mbps
Compliance	IEEE 802.3, 802.3u, 802.3x
Interface	Auto MDI/MDI-X
Operating Mode	Half-duplex or full-duplex
Address Table Size	1,024 MAC address entries with automatic learning and aging
Quality of Service	IEEE 802.1p priority, tag-based, 4 queues per port, weighted fair queuing scheduling
Maximum Frame Size	Untagged Ethernet frames up to 1,518 bytes Tagged Ethernet frames up to 1,522 bytes

## GENERAL

Operating Temperature	-40° to 167°F (-40° to 75°C)
Input Power Requirements	12 VDC or 24 VAC, 0.50 A
LED Indicators	Power 100Base-FX Port Status (link/activity, FEF1) Optic Fault (optic signal/laser status) 10Base-T/100Base-TX Port Status (link/activity and speed, duplex/collision and speed)
Dimensions	8.75" D x 1.08" W x 4.81" H (22.23 x 2.74 x 12.22 cm)
Unit Weight	1.6 lb (0.73 kg), approximate
Shipping Weight	3.0 lb (1.36 kg)

## MECHANICAL

Connectors	
Rack Power/Alarm	1, 4-pin connector
Stand-Alone Power	1, 2-pin connector, screw terminal
Electrical	1, RJ-45, 10Base-T/100Base-TX
Fiber Optic	1, dual-fiber ST or SC

## CERTIFICATIONS

- CE, Class A
  - UL Listed
  - UL Listed to Canadian safety standards
  - FCC, Class A
  - C-Tick
  - Complies with FDA requirements for Class 1 laser products
  - Designed to meet NEMA TS 2 and Caltrans traffic signal control equipment standards for ambient operating temperature, mechanical shock and vibration, humidity with condensation, high-line/low-line voltage conditions, and transient voltage protection (certification pending)
- Note:** Conformal coating is required for operation in environments with relative humidity above 95% (condensing).

## OPTIONAL ACCESSORIES

WM5001-3U	Wall mount base kit for single-width module
WM5001-3UEXP	Wall mount expansion kit for single-width module
RK5000-3U	19-inch rack mount chassis for 14 slots, no power (3 RUs)
RK5000PS-3U	19-inch rack mount chassis for 12 slots with power (3 RUs)
EPS5000-120	External rack power supply, 1 RU, dual 120 W power outputs
RK5001B-3U	Blank filler panel, single width
RK5002B-3U	Blank filler panel, double width
RK5001-1UEXP	Adapter kit that allows a 3 RU double-width fiber module to be used in RK5100PS-5U rack mount chassis



**Pelco, Inc. Worldwide Headquarters:**  
 3500 Pelco Way, Clovis, California 93612-5699 USA  
**USA & Canada** Tel: (800) 289-9100 • FAX: (800) 289-9150  
**International** Tel: +1 (559) 292-1981 • FAX: +1 (559) 348-1120  
[www.pelco.com](http://www.pelco.com)

Pelco and the Pelco logo are registered trademarks of Pelco, Inc.  
 Product specifications and availability subject to change without notice.  
 ©Copyright 2008, Pelco, Inc. All rights reserved.