



VBV-4 'NoCoax' Video Distributor Unit (VH30ANC and VH30CNC Series)



Architects' And Engineers' Specifications

The video data distributor unit(s) shall be Alpha Communications® / S.T.R.™ model **VBV-4**, or approved equal, and shall provide up to four (4) amplified video data outputs for the 'NoCoax' video-intercom system. The **VBV-4** shall be built into a rugged high impact ABS plastic case, and shall be powered by the model **NG20** DC power supply.

Low voltage wiring shall be used and positive screw terminal connectors shall be provided for installation wiring. The **VBV-4** shall be mountable right to the surface of the wall or in a customer supplied junction box cabinet.

Contractor shall observe all local and national electrical and building codes.

VBV-4 'NoCoax' Video Distributor Unit

The Alpha Communications® / S.T.R.™ **VBV-4** video distributor unit is used only with the **VH30ANC** and **VH30CNC** series 'NoCoax' video-intercom systems. The **VBV-4** is used when the video data signal from the lobby entry camera(s) must be split (distributed) to several cables.

The **VBV-4** gets its power from the **NG20** DC power supply. All **VBV-4** connections are positive screw terminal type.

Each **VBV-4** has four (4) video data outputs. When multiple **VBV-4**'s are used, for systems requiring more than four (4) outputs, multiple **VBV-4** units may be "daisy-chained" to provide outputs in multiples of four (4).

Features

- Easily Installs Right on Finished Wall Surface or in Optional Junction Box
- Operates on Safe Low-Voltage Class II Wiring
- Positive Screw Terminal Connectors
- Provides 4 separate amplified video data outputs
- Can be "daisy-chained" when more than 4 video outputs are needed

Specifications

Dimensions:	Height: 3.75" (96mm) Width: 4.25" (108mm) Depth: 2.375" (61mm) from mounting surface
Construction:	High impact Black ABS plastic case
Connections:	Positive screw terminal connectors
Temperature Range:	0-50 degrees C.
Mounting:	Surface-mounted (usually installed near the system amplifier/power supply and other system central equipment).

42 Central Drive • Farmingdale • NY • 11735-1202 • Phone: (631) 777-5500 • Fax: (631) 777-5599
TOLL-FREE: (800) 666-4800 • Web: AlphaCommunications.com • Email: info@alphacommunications.com

Copyright© 1998-2014 Alpha Communications® - All Rights Reserved.

Due to continuous product improvement, all colors, sizes, materials, finishes and specifications are subject to change without notice. [Next \(APS584\) >](#)

[< Previous \(APS582\)](#)