


# BATB Family Battery boxes\enclosures

www.boschsecurity.com



**BOSCH**  
Invented for life



- ▶ UL Approved as battery boxes and as enclosures for B9512G/B8512G/D9412GV4/D8412GV4/D7212GV4 control panels
- ▶ Suitable for residential/commercial fire or burglary applications
- ▶ Holds up to four auxiliary batteries

The BATB Family of battery box\enclosures is red for use in fire alarm systems. The BATB-40 provides a single level (two battery capacity) of battery storage. The optional BATB-SHELF battery shelf increases the battery capacity to four batteries. The BATB-80 comes with the BATB-SHELF mounted and holds up to four batteries.



#### Notice

The actual number of batteries the battery box can hold depends on the size of the batteries. For battery box dimensions, see Technical Specifications. Mounting requirements depend on the total weight of the battery box/enclosure. For mounting information, see the *BATB-40/BATB-80 Installation manual*.

They are UL listed for use as enclosures for B9512G/B8512G/D9412GV4/ D7412GV4/ D7212GV4 control panels.



#### Notice

When used as a control panel enclosure, the battery shelf must be removed.

### Certifications and approvals

Region	Regulatory compliance/quality marks	
USA	UL	ANSI/UL 864, Control Units and Accessories for Fire Alarm Systems
	UL	ANSI/UL 985, Household Fire Warning System Units
	CSFM	see <a href="http://www.boschsecurity.com">www.boschsecurity.com</a> (the Bosch website)

### Installation/configuration notes

#### Compatibility Information

The BATB Battery boxes/enclosures are compatible with the following products:

Category	Product Description
Batteries	D126 12 V, 7 Ah Battery D1213 12 V, 1.3 Ah Battery D1218 12 V, 18 Ah Battery D1222 12 V, 2.2 Ah Battery D1224 12 V, 24 Ah Battery D1238 12 V, 38 Ah Battery D1240 12 V, 4 Ah Battery D1250 12 V, 5 Ah Battery
Control Panels	D9412GV4 246-point Control Communicator D7412GV4 75-point Control Communicator D7212GV4 40-point Control Communicator

**Wiring Considerations**

For information on calculating the number and type of auxiliary batteries needed for your application and for wiring the auxiliary batteries, see the control panel's installation guide.



**Notice**

When using multiple batteries in a battery box, each battery must be the same voltage, rating, and type.

**Technical specifications**

**Battery Box Capacities**

**Batteries Storage - Total Dimensions (H x W x D)**

BATB-40 without shelf	22 in. x 20.75 in. x 7.25 in. (55.9 cm x 52.7 cm x 18.4 cm)
BATB-80 bottom	~14 in. x 20.75 in. x 7.25 in. (~35.6 cm x 52.7 cm x 18.4 cm)
On shelf	~8 in. x 20.75 in. x 7.25 in. (~20.3 cm x 52.7 cm x 7.25 cm)

**Number of Batteries**

BATB-40	Two
BATB-40 with shelf and BATB-80	Four

**Weight**

Combined total with batteries	140 lb. (63.5 kg)
On Shelf (maximum)	50 lb. (22.6 kg)

**Mechanical**

Color	Red
Dimensions (H x W x D)	22 in. x 21 in. x 7.5 in. (55.9 cm x 53.3 cm x 19 cm)
Material	18 gauge (1.2 mm) cold-rolled steel

**Weight**

• BATB-40 (without shelf):	28.5 lb (13 kg)
• BATB-40 (with shelf) and BATB-80:	33 lb (15 kg)

**Ordering information**

**BATB-40 Battery box/enclosure, 22x20.75x7.25"**

22 x 20.75 x 7.25" (56 x 53 x 18.5 cm). Holds two dry or wet cell batteries. Optional BATB-SHELF battery shelf increases number of batteries. Suitable for residential/commercial fire or burglary applications. Order number **BATB-40**

**BATB-SHELF Battery shelf, optional for BATB-40**

An optional battery shelf for the BATB-40. It allows up to two additional batteries to be placed in the battery box. Order number **BATB-SHELF**

**BATB-80 Battery box/enclosure, 14x20.75x7.25"**

14 x 20.75 x 7.25" (36 x 53 x 18.5 cm). Battery box/enclosure with shelf holds up to four dry or wet cell batteries. Suitable for residential/commercial fire or burglary applications. Order number **BATB-80**

**Accessories**

**D102 Replacement key for D101 lock set**

The D102 is a replacement key for locks stamped with 1358.

Order number **D102**

**Represented by:**

**Europe, Middle East, Africa:**  
Bosch Security Systems B.V.  
P.O. Box 80002  
5600 JB Eindhoven, The Netherlands  
Phone: + 31 40 2577 284  
emea.securitysystems@bosch.com  
emea.boschsecurity.com

**Germany:**  
Bosch Sicherheitssysteme GmbH  
Robert-Bosch-Ring 5  
85630 Grasbrunn  
Germany  
www.boschsecurity.com

**North America:**  
Bosch Security Systems, Inc.  
130 Perinton Parkway  
Fairport, New York, 14450, USA  
Phone: +1 800 289 0096  
Fax: +1 585 223 9180  
onlinehelp@us.bosch.com  
www.boschsecurity.us

**Asia-Pacific:**  
Robert Bosch (SEA) Pte Ltd, Security Systems  
11 Bishan Street 21  
Singapore 573943  
Phone: +65 6571 2808  
Fax: +65 6571 2699  
apr.securitysystems@bosch.com  
www.boschsecurity.asia